

Messages and Codes - EOR3101 - EOR5999

This subsection covers the following topics:

- Displaying a Long Message Text
- Messages EOR3101 - EOR5999 in Numerical Order

Displaying a Long Message Text

 To display a long message text

- Use the direct command

HELP MSG <message-code>

Messages EOR3101 - EOR5999 in Numerical Order

Message	Explanation	Action
EOR3101 - Please enter the Entire Operations Monitor batch module name	Entire Operations must know the module name of the linked batch Natural for the Monitor, to be able to restart it out of the System Administrator Services.	Correct error.
EOR3102 - Condition Retention Period too small	The active condition retention period must be greater or equal than the log retention period.	
EOR3103 - Active Jobs Retention Period too small	The retention period for active jobs must not be shorter than the retention period for active networks. See the field help for details.	
EOR3110 - Please confirm password change	A password has been modified. It must be entered twice for confirmation.	Please re-enter the password
EOR3111 - Invalid new password	The second entry of the new password did not match. The old password remains valid.	
EOR3200 - Invalid Node Number:1:		Enter a valid node number.
EOR3201 - Invalid Time Difference		Enter a time difference (in hours) in the range from -12 to +12.
EOR3202 - Please enter the node name		Correct error.
EOR3204 -:1:Nodes allowed	The maximum number of defineable Entire System Server nodes has been reached.	Contact Software AG support.
EOR3205 - VSE SysId must be 1 thru 9	The VSE SysId must be in the range 1 thru 9, or zero.	Enter a correct value.
EOR3206 - Server already defined		

EOR3211 - Broker Error:1:		
EOR3215 - Server:1:not in SATSRV	The operating system server name was not defined in Library SYSSATU, Member SATSRV.	Add a correct server entry in SYSSATU / SATSRV.
EOR3219 - Node:1:undefined	The node must be defined in the node table.	
EOR3220 - Node:1:Error:2:	An error occurred during access to an Entire System Server node. The Entire System Server error is shown in the message.	
EOR3221 - Node:1:not active		
EOR3222 - Node :1: Operating System :2: not supported		
EOR3225 - Node Name missing		
EOR3232 - Operating System Server:1:not supported		
EOR3338 - No match for:1:	No object was found for the specified search criteria.	
EOR3371 - Access denied for user:1:	The access to this object was denied due to the access rights of this object.	
EOR4000 - Editor Error::1:	An internal Editor error occurred. The message contains an error number or error text.	Contact Software AG support.
EOR4001 - Sysout browsing error:1:	An internal editor error occurred during the browsing of a job sysout. The message contains an error number or error text.	Contact Software AG support.
EOR4002 - Editor Open Error :1::2::3:	An internal editor error occurred.	Contact Software AG support.
EOR4003 - Editor Close Error :1::2::3:	An internal editor error occurred.	Contact Software AG support.
EOR4010 - Object cannot be edited from:1:	The object cannot be edited from this Natural environment.	
EOR4011 - Executable can not be edited		
EOR4101 - Editor Buffer Pool can not be used. RC =:1:	An Editor error occurred during space allocation in the Editor buffer pool. Processing continues. The Editor will allocate its work space elsewhere.	Contact Software AG support.
EOR4120 - Sysout of JobId:1:not found	The sysout of the job has already been deleted from the spool output. Browsing is no more possible.	
EOR4130 - SYSLST Begin		
EOR4131 - No SYSLST File Assignment found in Sysout		

EOR4132 - SYSLST File:	This message shows the current SYSLST file.	
EOR4133 - SYSLST Error:		
EOR4134 - SYSLST File empty		
EOR4139 - Unexpected Continuation of SYSFILE Assignment		
EOR4501 - No Symbol Table specified		Correct error.
EOR4502 - No Symbol Name specified		Correct error.
EOR4503 - No Symbol Value specified		Correct error.
EOR4510 - Symbol Table:1:empty	The requested symbol table contains no symbols.	Correct the symbol table name, or add symbols to the table.
EOR4511 - Symbol:1:not in Table:2:	A symbol could not be found in the defined symbol table.	Add the symbol to the table, or correct the symbol name.
EOR4512 - Symbol Name too long	A symbol name may not exceed 20 characters.	To separate the symbol from the following text, use a separator. A single dot after a symbol will be eliminated after replacement.
EOR4513 - Symbol:1:not found		
EOR4520 - Line too long after Replacement	One or more symbols have been replaced by their current values during the JCL generation. After the replacement, the resulting line is longer than allowed for the given operating system.	Split the JCL line and use continuations.
EOR4530 - No active Symbol Tables	No active symbol tables have been found for the selected network activation.	
EOR4550 - This is not a MACRO program	The job does not use the dynamic JCL generation.	
EOR4551 - Use MACRO Command for MACRO programs	Programs for the dynamic JCL generation may not be stowed. To compile the internal JCL generation routine, please use the MACRO Editor command.	Correct error.
EOR4552 - Use TEST command for MACRO programs	Programs for dynamic JCL generation cannot be checked for their syntax like normal Natural programs.	Use the Editor TEST command to see generated JCL.
EOR4553 - RUN command not possible for MACRO programs	Programs for dynamic JCL generation cannot be executed directly.	
EOR4554 - Use STRUCT command for Natural programs only	Only Natural programs may be structured with the STRUCT command.	

EOR4555 - Command failed - Source is already edited elsewhere.		
EOR4556 - #INCLUDE not found		
EOR5000 - Entire System Server Error:1:	An error occurred during the internal invocation of an Entire System Server function.	See the Entire System Server error messages for the message number. If this is a severe error, contact Software AG support.
EOR5100 - Access to ESY Node:1::2:OpSys:3:	The message is issued before the first access of the Entire Operations Monitor to an Entire System Server node.	
EOR5101 - Node:1:-	This Message contains an Entire System Server error text.	
EOR5102 - Node:1:disabled for Monitor	The node can no longer be accessed by the Entire Operations Monitor for any action.	
EOR5110 - Node Table Refresh demanded		
EOR5111 - Node Table Refresh for:1:demande		
EOR5509 - Logon failed, Node:1:, Id:2:	Entire Operations tried a Logon to an Operating System Server for a user ID on the node shown in the message. The current action was interrupted.	Check the user's security definitions.
EOR5510 - Logon required, Node:1:Id:2:	The Operating Server for the displayed node requires a Logon.	Use the 'LOGON SERVER ...' direct command for a logon to the node.
EOR5661 -:1:Natural Subtask already active	The Entire System Server subtask for the Entire Operations Monitor could not be started, because it is already active.	
EOR5697 - Library / Sublibrary not found		
EOR5995 - File not found	An invalid file name was entered.	Enter a valid name.
EOR5996 - Volume not online	Check for correct file and volume.	
EOR5999 - Entire System Server Node:1:not active	Entire Operations requested a function from an Entire System Server node, which is currently not active.	Start the Entire System Server node.